



**SmartGen**  
ideas for power

# BAC06N

## SWITCH-MODE BATTERY CHARGER

### USER MANUAL



**SMARTGEN (ZHENGZHOU) TECHNOLOGY CO.,LTD.**



Chinese trademark

**SmartGen** English trademark

**SmartGen** — make your generator *smart*

SmartGen Technology Co., Ltd.

No.28 Jinsuo Road

Zhengzhou

Henan Province

P. R. China

**Tel:** 0086-(0)371-67988888/67981888

0086-(0)371-67991553/67992951

0086-(0)371-67981000(overseas)

**Fax:** 0086-(0)371-67992952

**Web:** [www.smartgen.com.cn](http://www.smartgen.com.cn)

[www.smartgen.cn](http://www.smartgen.cn)

**Email:** [sales@smartgen.cn](mailto:sales@smartgen.cn)

All rights reserved. No part of this publication may be reproduced in any material form (including photocopying or storing in any medium by electronic means or other) without the written permission of the copyright holder.

Applications for the copyright holder's written permission to reproduce any part of this publication should be addressed to Smartgen Technology at the address above.

Any reference to trademarked product names used within this publication is owned by their respective companies.

SmartGen Technology reserves the right to change the contents of this document without prior notice.

Table 1 Software Version

Date	Version	Note
2020-05-09	1.0	Original release.



## CONTENTS

1	OVERVIEW.....	4
2	PERFORMANCE AND CHARACTERISTICS.....	4
3	CHARGING PRINCIPLES.....	4
3.1	TWO-STAGE CHARGING PRINCIPLE.....	4
3.2	THREE-STAGE CHARGING PRINCIPLE.....	5
4	SPECIFICATION.....	6
5	OPERATION.....	7
6	WIRING DIAGRAM.....	7
7	OVERALL DIMENSIONS AND INSTALLATION SIZE.....	8
8	MODELS.....	8

SmartGen

## 1 OVERVIEW

BAC06N battery charger adopts switching power supply device, and is specially designed for lead-acid battery used in engine start according to its property. The charger is suitable for long-term complement charging (floating) of lead-acid battery. The maximum output current for 12V charger is 6A; the maximum output current for 24V charger is 3A.

## 2 PERFORMANCE AND CHARACTERISTICS

Characteristics are as below:

- Applying switching power supply structure, wide range of AC voltage input, small volume, light weight and high efficiency;
- Automatic charging by selecting two-stage or three-stage charging method based on needs; two methods both are designed according to charging properties of the lead-acid battery, which can avoid overcharging and this extends the battery life to the fullest;
- Short circuit protection, reverse connection protection, absorption timing, and BOOST functions;
- LED status display: power indicator, and charging indicator;
- Applying horizontal installation, which is easy and simple to install.

## 3 CHARGING PRINCIPLES

### 3.1 TWO-STAGE CHARGING PRINCIPLE




Fig. 1 Two Stage Charging Principle

According to battery charging properties to conduct charging, if two-stage charging method is used, charging mode is "constant voltage/constant current mode". That is, before battery terminal voltage is lower than pre-set value, it is constant current charging, and current is 3A (6A). When battery terminal voltage is higher than the pre-set value, charging current decreases gradually as battery terminal voltage

increases until it reaches pre-set current value. At this time it turns to float mode and charging current reduces gradually. Battery terminal voltage also gradually increases to pre-set constant voltage value. Charging current is less than 0.4A (0.8A) and battery is basically full-charged (charge indicator is OFF). Afterwards charging current only offsets the self-discharging of battery and even long-term charging does no harm for the battery, that is, charger can not only maintain battery full-status, but also ensure the usage life of battery.

### 3.2 THREE-STAGE CHARGING PRINCIPLE




Fig. 2 Three Stage Charging Principle

According to battery charging properties to conduct charging three-stage charging method is used.


- Charging mode of first phase is "constant current mode". When battery terminal voltage is low, charging current is rated 3A (6A). Large current makes battery power rise rapidly. Above process is called bulk charging. Its characteristics is red charging indicator ON always.
- Charging mode of second phase is "absorption mode". After constant current charging, battery voltage rises to absorption voltage value. At this time battery keeps constant voltage output and charging current decreases slowly. Battery terminal voltage then keeps slowly at absorption voltage value. In this process red charging indicator is ON always. When absorption mode is reached, internal timer starts counting. When charging current drops to below 0.4A (0.8A), or about 3.5 hours, it turns to float charging mode.
- Charging mode of third phase is "float mode". After above two modes, power is basically full, and charger output voltage automatically transfers to float voltage 27.0V (13.5V), while current drops to below 0.4A (0.8A). Red charging indicator is OFF.

When charging current is above 2.6A (5.2A), charger enters absorption mode.

4 SPECIFICATION

Table 2 Product Parameters

Category	Items	12V Two-stage	12V Three-stage	24V Two-stage	24V Three-stage
Input Characteristics	Nominal AC Voltage	AC (100~277)V			
	Max. AC Voltage	AC (95~305)V			
	AC Frequency	50Hz/60Hz			
	Max. Input Current	2A			
	Max. Efficiency	85%		87%	
Output Characteristics	Rated Current	6A		3A	
	Float Voltage	13.8V	13.5V	27.6V	27.0V
	Absorption Voltage	/	14.4V	/	28.8V
	Max. Output Power	82W	87W	82W	87W
	No-load power consumption	<3W			
Insulation	Insulation Resistance	Between input and output, input and shell, input and BOOST all are: DC500V 1min R≥500MΩ			
	Insulation Voltage	Between input and output, input and shell, input and BOOST all are: DC4200V 50Hz 1min, between output and shell it is DC800V 1min, Leakage current: I≤3.5mA.			
EMC	EMC Emission	EN55032			
	EMC Immunity	IEC/EN61000-4-2,3,4,5,6,11 GB17626.2,3,4,5,6,11			
Working Conditions	Working Temperature	(-30~+55)°C			
	Storage Temperature	(-40~+85)°C			
	Working Humidity	20%RH~93%RH (No condensation)			
Profile	Weight	0.47kg			
	Dimension	136mm×86mm×49mm			
Mounting Size	Screw Mounting	Hole centres 77mm, suitable for M4;			



## 5 OPERATION




Fig. 3 BAC06N Panel

Table 3 Operation Illustration

Mark	Function	Description
L	AC input terminal	Terminal L and N connects AC (100-277)V; BVR1mm <sup>2</sup> multi-strand copper line is recommended.
N		
PE	GND connected terminal	Internally connected with shell;
BOOST	Charging phase mode	Three-stage: BOOST verse B- short circuit connection; Two-stage: BOOST hung up;
B-	Charger output negative	Connected with battery negative; BVR1.5mm <sup>2</sup> multi-strand copper line is recommended.
B+	Charger output positive	Connected with battery positive; BVR1.5mm <sup>2</sup> multi-strand copper line is recommended.
Power	Green LED indicator	Power status indicator;
Charging	Red LED indicator	Charging status indicator.

**NOTE 1:** Charger can be used with charger in the engine in parallel and there is no need to disconnect charger at cranking.

**NOTE 2:** For application on genset, as charging current is very big and voltage drop will produce from charging wires, so it is recommended to connect charging wire to battery terminal separately. The purpose of this is to avoid affecting sensor sampling precision.

## 6 WIRING DIAGRAM




Fig. 4 Wiring Diagram

## 7 OVERALL DIMENSIONS AND INSTALLATION SIZE




Fig. 5 Installation Size Drawing

**NOTE 1:** This charger is screw mounting designed, please use 2 pieces of M4 slots to fix.

## 8 MODELS

For ordering BAC06N chargers, please select based on charger battery voltage as Table 4.

Table 4 Charger Model

Model	Battery Type	Rated Output Current
BAC06N-12V	12V	6A
BAC06N-24V	24V	3A